

# TRACKSO INSTALLATION GUIDE FOR CROMPTON VFD

**Brand:** Crompton  
**Type:** VFD Drive  
**Models:** Emotron VSR Series

## CONNECTION DIAGRAM

The communication terminals (RS485) are located at the bottom of the drive. And there are two connection terminals on the configuration circuit board: RS485 A/B terminal blocks.




Figure C1– Communication Port of Crompton VSR Series

1. Press and hold in the tabs on each side of the cover. Pull the cover up to release keypad.
2. Locate the RS485 terminal (communication port 1) as shown in Figure C1.
3. Please make the connections from the Terminal Block of Crompton RS485 chipset to TrackSo IoT Gateway as mentioned in the Table – CT1
4. Provide 12-24V DC Supply to TrackSo at Pin no. 1 & 2.


Crompton RS485 Communication Card pin no. & Assignment	TrackSo Pin No. & Assignment	
485+	3	DATA+
485-	4	DATA-

● Rx
● Tx
● GSM
● PWR

**An IoT Platform for Energy Management**

Access installation guide at: [www.freespirits.in/trackso](http://www.freespirits.in/trackso)  
 For any enquiries, reach us at [we@freespirits.in](mailto:we@freespirits.in)

Inputs	AI-	8
	AI+	7
	DI-2	6
	DI-1	5
RS485	D -	4
	D +	3
PWR	GND	2
	+12V	1



### GPRS Enabled IoT Gateway for Remote Management

Table CT1 – Crompton RS485 chip connections with TrackSo IoT Gateway

## DEFAULT CONFIGURATION IN TRACKSO IOT GATEWAY

Inverter ID: **1, 2, 3, 4** .... Continuous numbering starting with 1, (**Range:** 1 to 247)

Baud Rate: **9600 (Default) (Values:** 9600, 19200, 38400)

Data Bits: 8

Stop Bit: 1

Parity: None

## CONFIGURATION AT THE AC DRIVE END

### How to operate Digital Keyboard

Symbol	Name	Function
	Escape	Enter or exit Level I menu
	Enter	Enter the menu interfaces level by level, and confirm the parameter setting
	Increment	Increase data or function code
	Decrement	Decrease data or function code
	Shift	Select the displayed parameters in the stop or running state, and select the digit to be modified when modifying parameters
	Multifunction	Perform function switchover (such as jog run and quick switchover of command source or direction) according to the setting of L0.00
	potentiometer	With the same function as AI1/AI2
	Run	Start the inverter in the keypad control mode
	Stop/Reset	Stop the inverter when it is in the running state and perform the reset operation when it is in the fault state. The functions of this key are restricted in L0.01.
	Key combinations	The inverter will coast to stop when the RUN and STOP key are pressed simultaneously



## SETTING THE BAUD RATE

This parameter is used to set the transmission speed between the RS485 master (PLC, PC, etc.) and AC motor drive.

← Set the baud rate to 9600

Parameter	Name	Settings	Factory Settings	Setting for TrackSo
H0.00	Baud Rate	0: Baud rate 4800bps 1: Baud rate 9600bps 2: Baud rate 19200bps 3: Baud rate 38400bps 4: Baud rate 57600bps 5: Baud rate 115200bps	1	1

## SETTING THE VFD ID

The communication address for each AC motor drive must be different and unique. Otherwise, the drive cannot be correctly identified.

Each VFD-E AC motor drive has a pre-assigned communication address specified by Pr.0H.02. The RS485 master then controls each AC motor drive according to its communication address.

← Set correct Ids

Parameter	Name	Settings	Factory Setting
0H.02	Communication Address	1 to 254	1

## SET COMMUNICATION PROTOCOL

A VFD-E can be set up to communicate in Modbus networks using one of the following modes: ASCII (American Standard Code for Information Interchange) or RTU (Remote Terminal Unit). Users can select the desired mode along with the serial port communication protocol in Pr.09.04.

Parameter	Name	Settings	Factory Setting	Setting for TrackSo
0H.01	Data Format	0: No check, data format (1-8-N-2) 1: Even parity check, data format (1-8-E-1) 2: Odd Parity check, data format (1-8-O-1) 3: No check, data format(1-8-N-1)  ~ all for RTU	0	3

The above details are mentioned in the [Installation & Operation Manual](#) for Crompton VFD.

## TRACKSO WORKING

1. Insure correct connections as detailed in the installation guide.
2. Insert the SIM card.




3. Switch on the power to the TrackSo device. (Minimum 12V/1A input is required)
4. Power LED (Red) of TrackSo IoT gateway glows and stays ON.

**NOTE:** TrackSo IoT Gateway will only be able to send data if the GPRS network is available at the installed location.

LED	NAME	DESCRIPTION														
GREEN	POWER	Light when Power on the device														
RED	GSM	<table border="1"> <thead> <tr> <th>LED Status</th> <th>Connection State</th> </tr> </thead> <tbody> <tr> <td>Flashing (ON for 100ms and OFF for 100ms)</td> <td>SIM Card not found</td> </tr> <tr> <td>Flashing (ON for 500ms and OFF for 500ms)</td> <td>Searching for GSM Network</td> </tr> <tr> <td>Flashing (ON for 0.1s and OFF for 2.9s) Once at every 3sec</td> <td>GSM Network Registered</td> </tr> <tr> <td>Flashing twice at every 3sec</td> <td>GPRS IP Connected</td> </tr> <tr> <td>Flashing 5times</td> <td>GPRS IP Sending data</td> </tr> <tr> <td>LED OFF</td> <td>GSM Fault</td> </tr> </tbody> </table>	LED Status	Connection State	Flashing (ON for 100ms and OFF for 100ms)	SIM Card not found	Flashing (ON for 500ms and OFF for 500ms)	Searching for GSM Network	Flashing (ON for 0.1s and OFF for 2.9s) Once at every 3sec	GSM Network Registered	Flashing twice at every 3sec	GPRS IP Connected	Flashing 5times	GPRS IP Sending data	LED OFF	GSM Fault
		LED Status	Connection State													
		Flashing (ON for 100ms and OFF for 100ms)	SIM Card not found													
		Flashing (ON for 500ms and OFF for 500ms)	Searching for GSM Network													
		Flashing (ON for 0.1s and OFF for 2.9s) Once at every 3sec	GSM Network Registered													
		Flashing twice at every 3sec	GPRS IP Connected													
		Flashing 5times	GPRS IP Sending data													
LED OFF	GSM Fault															
GREEN	COM TX	Blink on data transmission in RS485 port														
YELLOW	COM RX	Blink on data reception in RS485 port														

5. To check the exact network status send the following message to mobile number of the device



SMS Command= *2222#<Stat.gsm>	
IMEI	IMEI No. of the data logger (Device Key)
NW	Network
SIGN	Signal Strength out of 31
GPRS	CONT- connected , NC- not connected
PIP	Connected to TrackSo Server or not CONT- connected, NC- not connected
LOG	no. of data points stored in devices incase of no interet

- If the GSM light starts flashing 5 times then Login to [www.trackso.in](http://www.trackso.in) with your Username/Password.
- Click on 'Units' from the menu bar. You will be able to view your installed unit in the table as shown below.
- Check if the **Status** becomes **Receiving** for the relevant Unit.

Home / Units

Units Add Unit

Show 10 Search for...

Unit Name	Site	Unit Key	Category	Data Status	Last Event Timestamp	Device Key	Device Phone	Actions
1-Schnieder		[redacted]cc	Inverter	Receiving	2018-07-16 02:24:04	[redacted]31034235444/1	[redacted]9	View Data
2-Schnieder		[redacted]7799	Inverter	Receiving	2018-07-16 02:24:05	[redacted]034235444/2	[redacted]9	View Data
[redacted]	School	[redacted]5	Inverter	Not Receiving			[redacted]8	View Data
[redacted]	chool	[redacted]5	Inverter	Not Receiving				View Data

9. If the state remains **Not receiveing** for more than 10 minutes, click on your email ID at the top right of the screen and click on 'Event Ingestion Logs' in the dropdown.

Timestamp	Message	code
2018-07-16 02:42:16	Invalid request. Event should contain data. { "events": [{ "timestamp": 1531689133, "unit_key": "84f8b2c", "data": { } } ] }	not_acceptable
2018-07-16 02:41:13	Invalid request. Event should contain data. { "events": [{ "timestamp": 1531689070, "unit_key": "84f8b2c", "data": { } } ] }	not_acceptable
2018-07-16 02:40:10	Invalid request. Event should contain data. { "events": [{ "timestamp": 1531689007, "unit_key": "84f8b2c", "data": { } } ] }	not_acceptable

10. Check if there is some log generated at the time of installation of the TrackSo IoT Gateway device.
- If **NO**, please restart the device and try the same flow again.
  - If **YES**, email us at [support@trackso.in](mailto:support@trackso.in) to consult the same.